OT630E03CP 1/4



PRODUCT-DETAILS

# **OT630E03CP**

# OT630E03CP CHANGE-OVER SWITCH



General Information	
Extended Product Type	OT630E03CP
Product ID	1SCA022785R6050
EAN	6417019255965
Catalog Description	OT630E03CP CHANGE-OVER SWITCH
Long Description	630A, 3 pole manual change-over switch including a black plastic IP65 I-0-II pistol type handle (see the table below), shaft and bolt set for the cable connection. Handle padlockable in the 0-position, door interlock in the I- and II- positions and when padlocked.

Circular Value	
Environmental	1SCC303050D0201
Information	

## **Material Compliance**

Conflict Minerals 9AKK108467A5658
Reporting Template

OT630E03CP 2/4

$^{\prime\prime}$	М	DT	г١

REACH Declaration	1SCC011021D0201
RoHS Information	1SCC011020D0201
RoHS Status	Following EU Directive 2011/65/EU and Amendment 2015/863 July 22, 2019

# Ordering

Minimum Order Quantity	1 piece
Customs Tariff Number	85365080
Country of Origin	Finland (FI)

## Popular Downloads

Data Sheet, Technical Information	1SCC303003C0201
Instructions and Manuals	1SCC303008M0208

#### Dimensions

Product Net Width	311 mm
	12.24 in
Product Net Height	250 mm 9.84 in
Product Net Depth / Length	280 mm 11.02 in
Product Net Weight	15.37 kg 33.89 lb

#### Technical

rechnical	
Rated Operational Current AC-21A (I <sub>e</sub> )	(380 415 V) 630 A (500 V) 630 A (690 V) 630 A
Rated Operational Current AC-22A (I <sub>e</sub> )	(380 415 V) 630 A (500 V) 630 A (690 V) 630 A
Rated Operational Current AC-23A (I <sub>e</sub> )	(380 415 V) 630 A (500 V) 630 A (690 V) 630 A
Rated Operational Current AC-31B (I <sub>e</sub> )	(380 415 V) 630 A
Rated Operational Current AC-33B (I <sub>e</sub> )	(380 415 V) 630 A
Rated Operational Power AC-23A (P <sub>e</sub> )	(380 415 V) 355 kW (500 V) 400 kW (690 V) 630 kW
Conventional Free-air Thermal Current (I <sub>th</sub> )	Θ = 40 °C 630 A
Conventional Thermal Current (I <sub>the</sub> )	Fully Enclosed 630 A
Rated Impulse Withstand Voltage (U <sub>imp</sub> )	12 kV
Rated Insulation Voltage (Ui)	1000 V
Rated Operational	1000 V

OT630E03CP 3/4

		Voltage
for 1 s 20 kiloampe	for 1 s 20 kiloampere rms	Rated Short-time
		Withstand Current Low
		/oltage (I <sub>cw</sub> )
	25 W	Power Loss
	3	Pollution Degree
	Black	Handle Color
Handle and shaft in	Handle and shaft included	Handle Type
Mechanism at the End of the	Mechanism at the End of the Switch	Switches Operating
03 (Let	03 (Left Side)	Mechanism
St	Standard	Distance Between
		Phases
Top In - Bottom Out, Bottom In - T	Top In - Bottom Out, Bottom In - Top Out	Phases Position of Line
Top In - Bottom Out, Bottom In - T	Top In - Bottom Out, Bottom In - Top Out	
	Top In - Bottom Out, Bottom In - Top Out Front operated	Position of Line
Front op	Front operated	Position of Line Ferminals
Front op	Front operated	Position of Line Ferminals Operating Mode
Front op Base mo	Front operated Base mounting	Position of Line Ferminals Operating Mode Mounting Type
Front op Base mo	Front operated  Base mounting  3	Position of Line Ferminals Operating Mode Mounting Type Number of Poles
Front op Base mo	Front operated Base mounting 3 Front IP20	Position of Line Ferminals  Operating Mode  Mounting Type  Number of Poles  Degree of Protection

## Technical UL/CSA

Ampere Rating	630 A
Tightening Torque	acc. IEC 60947-1 50 75 N·m

#### **Environmental**

Environmental	1SCC303050D0201
Information	

### **Certificates and Declarations**

Declaration of Conformity - CE	1SCC303008D2703
DNV Certificate	1SCC303138D0201

## **Container Information**

Package Level 1 Units	1 piece
Package Level 1 Width	310 mm
	12.2 in
Package Level 1 Depth /	560 mm
Length	22.05 in
Package Level 1 Height	330 mm
	12.99 in
Package Level 1 Gross	18.51 kg
Weight	40.81 lb
Package Level 1 EAN	6417019255965

## Classifications

Object Classification

OT630E03CP 4/4

Code

ETIM 8	EC000216 - Switch disconnector
ETIM 9	EC000216 - Switch disconnector (low voltage)
eClass	V11.1 : 27371403
WEEE Category	5. Small Equipment (No External Dimension More Than 50 cm)
E-Number (Finland)	3641507

## Categories

 $Low\ Voltage\ Products\ and\ Systems \rightarrow Switches \rightarrow Change-over\ and\ Transfer\ Switches \rightarrow Manual\ Change-over\ Switches \rightarrow Cha$ 

