

Product datasheet

Specifications



MX shunt trip, GoPact MCCB 125, 110/415VAC 50/60Hz

G12SHT415AC

Main

Range of product	GoPact MCCB
product or component type	Voltage release
Device short name	MX
Device application	Control
Range compatibility	GoPact MCCB 125
Voltage release type	Shunt trip
[Uc] control circuit voltage	110...415 V AC 50/60 Hz

Complementary

Threshold tripping voltage	0.7...1.1 Un opening
Max supply pick-up power consumption	5 VA
Response time	25 ms

Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	6.5 cm
Package 1 Width	8.5 cm
Package 1 Length	4.8 cm
Package 1 Weight	900 g
Unit Type of Package 2	S02
Number of Units in Package 2	20
Package 2 Height	15 cm
Package 2 Width	30 cm
Package 2 Length	40 cm
Package 2 Weight	2.115 kg
Unit Type of Package 3	P06
Number of Units in Package 3	320
Package 3 Height	60 cm
Package 3 Width	60 cm
Package 3 Length	80 cm

Price is "List Price" and may be subject to a trade discount – check with your local distributor or retailer for actual price.

Package 3 Weight

42.34 kg

Sustainability

Green Premium™ label is Schneider Electric's commitment to delivering products with best-in-class environmental performance. Green Premium promises compliance with the latest regulations, transparency on environmental impacts, as well as circular and low-CO₂ products.

Guide to assessing product sustainability is a white paper that clarifies global eco-label standards and how to interpret environmental declarations.

[Learn more about Green Premium >](#)

[Guide to assess a product's sustainability >](#)



Transparency RoHS/REACH

Well-being performance

 Mercury Free

 Rohs Exemption Information [Yes](#)

 Pvc Free

Certifications & Standards

Reach Regulation [REACH Declaration](#)

Eu Rohs Directive Compliant with Exemptions

China Rohs Regulation [China RoHS declaration](#)

Environmental Disclosure [Product Environmental Profile](#)

Weee The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins

Circularity Profile [End of Life Information](#)