


# Product datasheet

Specifications



## MX shunt trip, GoPact MCCB 400/800, 240VAC 50/60Hz

G40-80SHT240AC

### Main

Range of product	GoPact MCCB
product or component type	Voltage release
Device short name	MX
Device application	Control
Range compatibility	GoPact MCCB 400 GoPact MCCB 800 EasyPact Solar MCCB 400 EasyPact Solar MCCB 800
Voltage release type	Shunt trip
[Uc] control circuit voltage	240 V AC 50/60 Hz

### Complementary

Threshold tripping voltage	0.7...1.1 Un opening
Max supply pick-up power consumption	5 VA
Response time	25 ms

### Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	6.5 cm
Package 1 Width	8.5 cm
Package 1 Length	4.8 cm
Package 1 Weight	110 g
Unit Type of Package 2	S02
Number of Units in Package 2	20
Package 2 Height	15 cm
Package 2 Width	30 cm
Package 2 Length	40 cm
Package 2 Weight	2.515 kg
Unit Type of Package 3	P06
Number of Units in Package 3	320
Package 3 Height	60 cm
Package 3 Width	60 cm

---

**Package 3 Length** 80 cm

---

**Package 3 Weight** 48.740 kg

## Sustainability

**Green Premium™ label** is Schneider Electric's commitment to delivering products with best-in-class environmental performance. Green Premium promises compliance with the latest regulations, transparency on environmental impacts, as well as circular and low-CO<sub>2</sub> products.

**Guide to assessing product sustainability** is a white paper that clarifies global eco-label standards and how to interpret environmental declarations.

[Learn more about Green Premium >](#)

[Guide to assess a product's sustainability >](#)



Transparency RoHS/REACH

## Well-being performance

Mercury Free

Rohs Exemption Information [Yes](#)

Pvc Free

## Certifications & Standards

Reach Regulation [REACH Declaration](#)

Eu Rohs Directive Compliant with Exemptions

China Rohs Regulation [China RoHS declaration](#)

Environmental Disclosure [Product Environmental Profile](#)

Weee The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins

Circularity Profile [End of Life Information](#)